

SPECIALIZED POWER



25.6V 200Ah LiFePO4 Battery Specification

25.6V 200Ah

Battery Model: 25.6V200AH
Battery Material: LiFePO4
Nominal Voltage: 25.6V
Nominal Capacity: 200AH

SPECIALIZED POWER

✓ Product Picture



Stock image may vary, multiple case options available

✓ Specification

Item	Specification
Cell Type	CATL Brand LiFePO4 Prismatic Cell
Nominal Capacity	200Ah
Nominal voltage	25.6V
Charge Cut-off Voltage	29.2V
Discharge Cut-off Voltage	20.0V
Maximum Charge Current	100A
Continuous Discharge Current	150A (200A Optional)
Peak Discharge Current	300A
Communication Port	RS485
SOC Display	LCD Voltage Display
Battery Housing	Metal case, white
Operating temperature	Charging: 0°C~45°C
	Discharging: -10°C~60°C
Storage temperature	-5°C~35°C
Storage Humidity	≤75% RH
Environmental condition	Temperature: 25±2°C
	Humidity: 45-75%RH
	Atmospheric Pressure: 86-106 KPA
Discharge/Charge connector	Screw In Terminals
Size (Custom Cases Available)	500 (L) x 260 (W) x 230 (H) (mm) 20(L) x 10.2 (W) x 9 (H) (inches)
Net Weight	Approx.: 50kg / 110lbs

SPECIALIZED POWER

General Performance

Item	Test Methods and Condition	Criteria
0.2C Capacity	After standard charging, hold battery for 10mins, then discharge at 0.2C to voltage 21.0V, recording the discharging time.	≥201Ah
Cycle Life	Constant current 0.2C charge to 29.2V, then constant voltage charge to current declines to 0.01C, rest 10min constant current 0.5C discharge to 20.0V rest 10min. Repeat above steps till continuous discharging capacity Higher than 70% of the Initial Capacities of the Cells	≥5000 times
Capability of storing electricity	20+/-5°C, After standard charging, hold the battery for 28days, then discharge at 0.2C rate to voltage 21.0V, recording the discharging time.	≥240min

✓ Environment Performance

Item	Test Methods and Condition	Criteria
Discharge at high temperature	After standard charging, shelve the cells 4h at 60+/-2°C, then discharging at 1C to voltage 21.0V, recording the discharging time.	≥54min
Discharge at low temperature	After standard charging, shelve the cells for 16h at -20+/-2°C, then discharging at 0.2C to voltage 21.0V, recording the discharging time.	≥210min
Thermal shock	Put the battery cells in the dryer box. The temperature of the oven is to be raised at 5+/-2°C per minute to a temperature of 100+/-2°C and remains 30 minutes.	No fire, no smoke

✓ Safe Characteristic

Item	Test Methods and Condition	Criteria
Over charge testing	At 23+/-5°C, charging cells with constant current 2C to voltage 29.2V, Stop test till cells temperature 10°C lower than max temperature.	No smoke or fire

SPECIALIZED POWER

Over discharge testing	At 23+/-5°C, According to the requirements of standard charge, the cells will be discharge to cut-off voltage, then connect with external load of 30 ohm for 24 hours.	No fire, no smoke, no leakage.
Short-circuit testing	At 23+/-5°C, After standard charging, connect cells anode and cathode by wire which impedance less than 200+/-20m Ω, shelve the battery for 6 hours.	No smoke or fire

※Above testing of safe characteristic must be with protective equipment.

CAUTIONS IN USE

To ensure proper use of the battery please read the manual carefully before using it. Handling ▪
Do not expose to, dispose of the battery in fire.

- Do not put the battery in a charger or equipment with wrong terminals connected.
- Avoid shorting the battery
- Avoid excessive physical shock or vibration.
- Do not disassemble or deform the battery.
- Do not immerse in water.
- Do not use the battery mixed with other different make, type, or model batteries.
- Keep out of the reach of children.

✓ **Charge and Discharge**

- Battery must be charged in appropriate charger only.
- Never use a modified or damaged charger.
- Do not leave battery in charger over 24 hours.

✓ **Storage**

- Store the battery in a cool, dry and well-ventilated area.

✓ **Disposal**

- Regulations vary for different countries. Dispose of in accordance with local regulations.

✓ **Battery operation instruction**

★ **Charging**

Charging current Cannot surpass the biggest charging current which in this specification book stipulated.

SPECIALIZED POWER

Charging voltage Does not have to surpass the highest voltage range which in this specification book stipulated.

Charge temperature The battery must carry on the charge in the ambient temperature scope which this specification book stipulated.

Uses the constant electric current, and the constant voltage way charge, the prohibition reverse charges. Incorrect connection of the battery positive electrode and the negative terminal can damage the battery.

★ Discharging current

The discharging current does not have to surpass this specification book stipulation the biggest discharging current, the oversized electric current electric discharge can cause the battery capacity reduction and to cause the battery overheat.

★ Discharge temperature

The battery discharge must carry on in the ambient temperature scope which this specification book stipulated.

★ Over-discharges

After the short time excessively discharges charges immediately cannot affect the use, but the long time excessively discharges can cause the battery the performance, battery function losing. The battery long-term has not used, has the possibility to be able to be at because of its automatic flashover characteristic certain excessively discharges the condition, for prevented excessively discharges the occurrence, the battery should maintain the certain electric quantity.

★ Storing the Batteries

The battery should store in the product specification book stipulation temperature range. If has surpasses above for one months the long-time storage, suggested you should carry on additional charge to the battery.

✓ **Other The Chemical Reaction**

Because batteries utilize a chemical reaction, battery performance will deteriorate over time even if stored for a long period of time without being used.

In addition, if the various usage conditions such as charge, discharge, ambient temperature, etc. are not maintained within the specified ranges the life expectancy of the battery may be shortened or the device in which the battery is used may be damaged by electrolyte leakage. If the batteries cannot maintain a charge for long periods of time, even when they are charged correctly, this may indicate it is time to change the battery.

SPECIALIZED POWER

✓ NOTICE

Before using the battery pack/packs, pls DO NOTE BELOW REMINDINGS:

Battery appearance visual check:

Carefully open the protective carton/wooden box Once batteries received.

Pls do check if the batteries with any scratches or impacted.

If everything goes well, pls go on.

If any, pls contact us at the very first time without any delay.

Do correctly connect the battery with Positive Pole and Negative Pole (usually Red + Black -).

Otherwise short circuit would possibly happen due to wrong connection on +/- terminal.

Connection Use Notice:

Do keep the battery packs within 1.0VDC voltage difference if you are going to connect them in series or parallel. The smaller voltage difference (0.1V-1.0V) of the battery packs the better for batteries connection.

DO NOT discharge the battery pack till 0% Power which is not that good to keep longer life.

Pls charge the battery to 80% (100% would also be fine) and DO Recharge the Battery while they are discharged/used down to 20% Power.

DO Recharge the Battery Packs every 3 months if they are shelved/not used for long time.
